

LHD8001



Features:

- 16 wireless zone, 4 wired zone, can compatible with all kinds of wireless and wired detector.
- LCD display, friendly English guidance for operation
- smart program: the user can set the parameter freely.
- Compatible with communication protocol: ADEMCO 4+1 Contact ID, It can be used by single or net alarm system. Automatically dial alarm center, user cell phone or fixed telephone with audible alarm while emergencies happen.
- Alarm received phones: 1 in alarm center and 5 common telephones.
- 7 codes: 1 user code, 1 duress code, 5 operator code.
- Wireless code learns restoring and reading function with simple usage
- 5 remote control panel at most.
- Arm & disarm using 5 wireless remote controllers on the spot.
- Several alarm modes: alarm bell and voice alarm
- Three groups timed auto arm/disarm time
- Protection zone valid/bypass selectable, user can set alarm area as desired.
- Restore user password to factory defaults by hardware and restore the system factory defaults by software.
- Record 40 latest alarm events
- Malfunction alarm: AC power fail, low voltage and telephone line loss
- Set real-time clock inside
- Auto-recording function, record the address of the alarm and other information
- Programmable relay output
- Anti-tamper function of the control panel
- Field monitor function

Technical Parameters:

- Power adapter working voltage: AC100V ~ 240V
- Operating voltage of the control panel: 12VDC
- Static operating current: $\leq 130\text{mA}$
- Bell output current: $\leq 400\text{mA}$
- Dimension: 250x150x45mm
- Wireless frequency: 315 MHz/433MHz/868MHz
- detector receive range: $\leq 90\text{m}$ (no obstacle)
- remote control valid range: $\leq 50\text{m}$ (no obstacle)
- record time 4 second