

Outdoor Bell Box BX-11



- **Two-Way Radio Communication**
- **Dual Frequency Hopping**
- **Code Encryption**

Battery-operated, completely wire-free operation with a 3-year battery life guarantee. BX-11 is innovated with a siren and strobe light for outdoor use to attract attention by using **Bi-directional** radio communication. It also features **Dual Frequency Hopping** and **Code Encryption** to ensure infallible signal transmission to and from the Control Panel.

Features:

- Bi-directional Radio Communication
- Dual Frequency Hopping & Code Encryption
- Waterproof & UV Proof with **IP rating 43**
- Battery operated with life expectancy of > 3 years in a typical domestic environment
- Low Battery detection and reporting to control panel
- Tamper protection protects the enclosure from being opened or removed from it's mounting surface and reporting to control panel
- Randomized **Supervision** signals for trouble-free system integrity checking
- **Jamming Detection** to protect from unauthorized interference
- System Status Indicator with siren beeps and strobe light
- Automatic Siren Cut-Off at selectable durations of 3 / 5 / 10 minutes
- Strobe Light Control can be selectable between Auto Cut-off or Manual Cut-off

Specifications:

- Power: Alkaline D batteries x 4
- Battery life: 3 years or over¹
- Siren output: 104dB @ 1 meter
- Radio frequency available: 868.6375 / 868.6875 MHz Narrow FM
- Range: over 300 meters in open space
- Operating temperature: -20° to 50°C
- Humidity: up to 95% non-condensing
- Dimensions: 257 X 220 X 69 mm

* Note¹: Battery life is calculated at an average of 2 activations per day.

