

## **Remote Keypad KP-18 & KPA-18** **– Easy to install, simple to use, and full system power at your fingertips!**

- **Two-Way Radio Communication**
- **Full Text LCD Display**
- **Firmware upgrade available**



KP-18 features a 16 x 2 characters full text LCD display as well as Two-Way Radio Communication, leaving user in no doubt as to whether the alarm system has been successfully armed or not.

It shows **Exit Delay Time** when the system is successfully armed, and also able to check the system status and report any sensor or device fault by displaying Error message on the LCD.

Safeguarded by a **Tamper Proof Switch**, protects the enclosure from being opened or removed from the mounting surface. **Power conservation** is another design feature; the Remote Keypad consumes power only when in operation, thus ensuring long battery life.

### **Features:**

- A 16 x 2 characters full text LCD display for status & fault indicator
- Dual key operation for activation of **Panic, Fire, and Medical** alarms
- Built-in speaker with Door Chime, Entry / Exit Delay sound indication
- A 16-button **backlit keypad** for easier night use
- Power conservation that consumes power only when in operation
- Low Battery detection
- Tamper protection protects the enclosure from being opened or removed from it's mounting surface
- Compact & low profile
- Designed to work with NXP Control Panels
- Can be used to program NXP Control Panels without LCD display

- Firmware upgradeable via NXP Control Panels
- Complied with CE requirements

**Specifications:**

- Power: Lithium AA battery x 1 (AC adaptor optional)
- Battery life: 3 years or over<sup>1</sup>
- Radio frequency available:
 

KP-18-433:	433 MHz
KP-18-868:	868.6375 MHz Narrow FM
KPA-18:	868.35 MHz
- Range:
 

433 MHz or 868.35 MHz:	over 200 meters in open space
868.6375 MHz:	over 300 meters in open space
- Operating temperature: -20° to 50°C
- Humidity: up to 95% non-condensing
- Dimensions: 145 X 89.1 X 24.6 mm

\* Note<sup>1</sup>: Battery life is calculated at an average of 4 activations per day.

Technoshield Security Systems  
 Website: <http://www.cyprussecurityspecialists.com>  
 Email: [sales@cyprussecurityspecialists.com](mailto:sales@cyprussecurityspecialists.com)

