



UR-7/UR-8

Universal Receiver UR-7, UR-8 & URA-8

Universal Receiver is specially designed to add wired auxiliary devices to a wireless Control Panel. When an alarm is triggered, the Control Panel will signal the Universal Receiver to activate the auxiliary devices for immediate corresponding reactions.

Features:

- * Output: Dry contact relay
- * Contact Capacity: 0.5A 125V AC, or, 1A 30V DC
- * Output mode: Latch / Unlatch / Pulse, programmable
- * Signal to Action: Burglar / Fire / Water / All alarm, programmable

Specifications:

- * Power: 12V DC Power Adaptor

* Radio frequency available: UR-7: 433 MHz

UR-8: 868.6375 MHz FM

URA-8: 868.35 MHz

* Range: 433 MHz or 868.35 MHz: over 200 meters in open space

868.6375 MHz: over 300 meters in open space

* Operating temperature: -10° to 45°C

* Humidity: up to 90% non-condensing

* Dimensions: 100 X 56 X 23 mm

Technoshield Security Systems
Website: <http://www.cyprussecurityspecialists.com>
Email: sales@cyprussecurityspecialists.com

