

IDO9008EV



8-channel D1 Real-time Standalone DVR, Support VGA output

Key Specifications/Special Features:

- ☐ Support 2 channels Full D1 realtime + 6 channels full CIF realtime recording resolution, ahead to D1 high-definition period
- ☐ Graphics and windows OSD interface, intuitive user-friendly navigation menu
- ☐ Dual-stream design, network remote view effects and local recording effects parameters can be set separately, independently of each other
- ☐ Display frame rate:
 - ☐ NTSC: 240fps
 - ☐ PAL: 200fps
- ☐ Recording frame rate:
 - ☐ NTSC: 240fps
 - ☐ PAL: 200fps
- ☐ 8-channel video input, 1-channel video output, 1-channel audio-in, 1-channel audio-out
- ☐ 1-channel alarm-in, 1-channel alarm-out
- ☐ Multiplex function: live display, record, playback and network live, playback, backup simultaneously, independently of each other
- ☐ Support Multiple channel playback simultaneously, to facilitate comparison the different channels of recording of recording (support 8-channel playback simultaneously and each channel can be enlarge to full screen)
- ☐ Super Network function: one IE browser centralized monitoring and CMS Software for multiple DVR (up to control 255 DVR simultaneously)
- ☐ Supports multiple backup mode: USB flash drive, USB hard disk and network backup
- ☐ Support full control through USB Mouse, finishing all the setup and operating
- ☐ Support remote view by mobile phone (support Symbian S60 Microsoft's Windows CE, Apple's iPhone, RIM's BlackBerry and Android system)
- ☐ Support One SATA HDD, unlimited for the capacity
- ☐ Support PTZ control via built-in RS-485 port
- ☐ Support VGA output

